





INVERTER GENERATOR 3000 VIGI3000

The VITO's Inverter Generator (VIGI3000) features a 4-stroke, 5.8 hp | 4.3 kW petrol combustion engine and has a 5-hour continuous running time. Its inverter technology makes the generator more efficient, keeping the electric current supplied stable and without oscillations. It is suitable for various types of uses, from home, garden, camping, caravans, among others. This equipment is silent and has electric start, 2 AC 230V sockets, a nominal power of 3.2 kW and a maximum power of 3.5 kW. Furthermore, it is equipped with oil level and current overload warning indicator lights. With a compact and portable design, the inverter generator has an aluminium handle and two wheels for safe transportation of the machine.

Key features

- > Suitable for:
- > Home;
- > Garden;
- > Camping;
- > Caravans;
- > Stable electric current without oscillations;
- > Silent and more efficient in terms of consumption;
- > Lightweight and easy to transport;
- > Easy and smooth / fast electric start.







Specifications

-	
Autonomy	5 h / 100% - 8.5 h / 50%
DC terminals thermal protection	8,3 A
Dimensions	590 x 456 x 511 mm
Engine	4st combustion
Engine displacement	212 cc
Fuel	Petrol 95
Max. Power	3.5 kVA
Maximum power - AC sockets	3.5 kW
No-load Speed	3600 rpm
Power factor (cos Ø)	1
Product weight	45 kg
Rated current - AC sockets	15,2 A
Rated power	5.8 cv / 4.3 kW
Rated power - AC sockets	3.2 kW
Rated voltage - DC terminals	12 V
Sound power level (LWA)	95 dB
Tank capacity	8,3 L

Package Contents

> Oil funnel > DC output cable
> DC output cable
> 16A schuko plug
> Set of wrenches
> Instruction manual.

October 26, 2025, 11:31h

VITO - Tools for the brave | Subject to correction or change without prior notice.